



WEC-2RC is a highly programmable remote-control device to change the default settings of compatible sensors.

Remote Control Setting	Button	Name	Description										
	Transmit	Transmit	Uploads the settings										
	Detection Area	Detection Area	25% / 50% / 75% / 100%										
	Hold time	Hold time	The timeout from 100% to dim 8S/1min/5min/15min/30min										
	Daylight Threshold	Daylight Threshold	5Lux/15Lux/50Lux/150Lux/ Disable										
	Stand-by period	Stand-by period	The timeout from dim to off 0S/1min/5min/30min/∞										
	Stand-by DIM level	Stand-by DIM level	10% / 20% / 30% / 40% / 50%										
	Auto mode	Auto mode	A. Movement Motion detect 9.8ft-19.7ft/3-6m B. Presence detect 9.8ft-19.7ft/3-6m C. Presence detect with daylight harvesting 9.8ft-19.7ft/3-6m D. High mounting: 19.7ft-49.2ft/6-15m E. High mounting with daylight harvesting : 19.7ft-49.2ft/6-15m										
	ON-OFF	ON-OFF	Permanent ON/OFF										
	Reset	Reset	Press "Reset" button for factory testing purpose only. <table border="1"> <thead> <tr> <th>Detection Area</th> <th>Hold Time</th> <th>Daylight sensor</th> <th>Stand-by period</th> <th>Stand-by dim level</th> </tr> </thead> <tbody> <tr> <td>100%</td> <td>1min</td> <td>Disable</td> <td>3min</td> <td>20%</td> </tr> </tbody> </table>	Detection Area	Hold Time	Daylight sensor	Stand-by period	Stand-by dim level	100%	1min	Disable	3min	20%
Detection Area	Hold Time	Daylight sensor	Stand-by period	Stand-by dim level									
100%	1min	Disable	3min	20%									
	Ambient Threshold	Ambient Threshold	Press this button to set the current suitable daylight threshold.										
	Dim+ / Dim -	Dim+ / Dim -	Adjust the light level when motion detected.										
	*1/2/3/4	*1/2/3/4	4 optional quick settings										

WEC-2RC

Compatible with

WEC-2MDR-36

Batteries

2 AAA Batteries (Not Included)