

AWARNING

- 1. Risk of electrical shock. Disconnect power before servicing or installing product.
- 2.Risk of injury or damage. Unit will fall if not installed properly. Follow installation instructions.
- 3. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and thehazards involved.
- 4. Risk of injury. Wear safety glasses and gloves during installation and servicing.





TO INSTALL:


1. Drill a **3.0"** open hole in the ceiling to mount fixture. If the size of open hole in the ceiling is less than 3.0", make sure larger than 2.6". Clean all areas that will be sealed. (See Fig.1)


NOTE: Luminaire can be mounted to an existing hole in canopy up to 4" diameter.


- 2. Lift the luminaire to the 3"open hole. Pass wires or cables through the ceiling. Do not pinch or trap wires between luminaire and ceiling. (See Fig.2)
- 3. Mount the luminaire using the customer supplied screws. (See Fig.3)
- 4,Clean the above of the canopy,Seal the plate ,Using 4pcs provided screw nuts to tighten the plate . (See Fig.4)
- 5, From above canopy feed leads from luminaire through supplied 1.0" NPT Stem. Screw supplied NPT Stem into luminaire hub. (See Fig.5)
- 6, Attach supplied junction box to the other end of the supplied 1.0" NPT Stem and make wiring connections into supplied junction box (See Fig. 6.7 and 8)












ELECTRICAL CONNECTIONS:

- a. Connect the black wire to line
- b. Connect the white wire to neutral
- c. Connect the green or green/yellow wire to ground

HOT BLK NEU WHT GRND REN,GRN/YEL

PRODUCT DIMENSIONS:



Attention:

Picture 7

