WESTGATE

MODELS:

LMW-EMB;LMW-EMB-WH

1. Installation

Warning:

To avoid the risk of fire, explosion, or electric shock, this product should be installed, inspected, and maintained by a qualified electrician only, in accordance with all applicable electrical codes.

Warning:

To avoid electric shock:

•Be certain electrical power is OFF before and during installation and maintenance.

•Luminaire must be connected to a wiring system with an equipment-grounding conductor.

Warning:

To avoid explosion:

•Make sure the supply voltage is the same as the rated luminaire voltage.

•Do not install where the marked operating temperatures exceed the ignition temperature of the hazardous atmosphere.

•Do not operate in ambient temperatures above those indicated on the luminaire nameplate. •Keep lens tightly closed when in operation.

For supply connections use wire rated for at least 100°C

Installation:

Step 1: Loosen the screw which beside the lens, take down the base plate (FIG.1)

Step 2: Fix the base plate with EVA on to the wall by 4 screws (FIG .2) Step3: loosen the screw which beside the lens, take down the base plate (FIG.3)

Step 4: Fix LED mounting plate to EM back box by 4 screws(FIG.4)

Step 5: Fix whole fixture on to EM back box , then overall fix to FIG.2 mounting plate ,complete the wiring (FIG.5)

Step 6: Seal with glue into the connective position between fixture and EM back box to waterproof (FIG. 6)

Step 7: Seal with glue into the connective position between EM back box and the wall to waterproof (FIG.7)





















After installation, please

- □ check whether the lighting fixture is firmly fixed.
- Check whether wires are connected correctly.

<u>At last, turn on the power, and check if the lighting fixture works well. If not, please turn off the power and contact with local dealer.</u>